

LED GX53

Key

1 to 6

Dimmable, with one to six lamps

The dimmer is not tested or not recommended

Manufacturer	Model No.	Voltage (V)	Wattage (W)	LR2205d		LR3307d	
Altenburger	50.04.000	220	60-600				1 to 6
Altenburger	EHR600W	220-240	60-600		1 to 6		1 to 4
Altenburger	Sim2A	220	60-400		1 to 6		1 to 6
Anam	ASW 3000-1	220-240	60-1000		1 to 6		1 to 6
Aurora	AU-DSP400	240	60-400		1 to 6		
Aurora	AU-DSP400X	240	60-400		1 to 6		1 to 6
Aurora	AU-DSP400X	230	60-400				1 to 6
British General	881P-01	240	60-400				1 to 6
British General	AT091-BG	200-250	60-500		1 to 6		1 to 6
Broco	F25AF	220-240	60-500		1 to 6		1 to 6
Bticino	CW20 802	250	400		1 to 6		1 to 4
Bticino	L4581	220-230	50-1000		1 to 6		1 to 6
Bticino	M9350S	220-240	500		1 to 6		1 to 6
Busch	2210..-510	220-240	60-400		1 to 6		1 to 6
Busch	2210-510	220-240	400		1 to 6		1 to 6
Busch	2250U	220-240	60-600		1 to 6		1 to 6

Compatible Dimmer List

LED GX53

LED by
MEGAMAN®

		LR2205d		LR3307d	
Manufacturer	Model No.	Voltage (V)	Wattage (W)		
Busch	6524U	230	2-100	1 to 4	
Chengli	27V500	250	500	1 to 6	
China IDV	IKT02	220	500	1 to 6	1 to 6
China IDV	Mosaic	220	500	1 to 6	
Click	MD9042	220-240	60-400		1 to 6
Clipsal	3031V500M/K	250	500	1 to 6	1 to 6
Clipsal	32E450LM	220-240	20-450		1 to 1
Clipsal	32E450UDM	220-240	450	2 to 6	
Clipsal	32E450ULM	220-240	450	1 to 6	
Clipsal	32V 500 Series	220-240	500	1 to 6	1 to 6
Clipsal	E3032V500	250	500		1 to 4
Clipsal	F50RD400M	220	400		1 to 4
Clipsal	KB31-RD400	220-240	400	1 to 3	1 to 6
Clipsal	S//E32	250	500	1 to 6	1 to 6
Contactum	P400	216-253	60-400		1 to 6
Crabtree	CRO-1W400	220-240	10-600		1 to 3
Danlers	DP1DLED	230	5-250		1 to 6
Danlers	DR1D400w	230	60-400		1 to 4
Denmans	HDP-400	200-240	60-400	1 to 6	
Deta	DEP-400DT	200-240	35-400		1 to 6
Doyle & Tratt Products	7066	220-240	40-250	1 to 6	

Compatible Dimmer List LED GX53

LED by
MEGAMAN®

		LR2205d		LR3307d	
Manufacturer	Model No.	Voltage (V)	Wattage (W)		
Doyle & Tratt Products	P400	220-240	60-400	1 to 6	1 to 6
Düwi	8050	230	40-400		1 to 6
Düwi	11442	230	50-300		1 to 6
Düwi	Grundtyp D1	230	60-300		1 to 6
Düwi	Grundtyp H1	230	20-500	1 to 6	1 to 6
Eagltrise	SED300FHS	220-240	60-300	1 to 6	1 to 6
Elari	ATD300R	230	300		1 to 6
Elko	400GLI	220-240	40-400	1 to 6	1 to 6
Everflourish	EFO700DA	220-240	50-300	1 to 6	1 to 6
Fungyip	F2771	220-240	500	1 to 6	1 to 5
GE	37/56	230	40-500	1 to 6	1 to 6
GET	EN60669	220-240	250	1 to 6	1 to 6
Gewiss	GW 20 803	230	300	1 to 6	1 to 6
Gira	03000	230	20-500	1 to 2	
GP	GP300	250	300	1 to 6	
Hamilton	L400/2	220-240	400		1 to 6
IKEA	E0902-DIM	220-240	25-150	1 to 6	1 to 4
Insta	Gira 1176 00/ I00	230	50-420	1 to 6	1 to 3
Jung	244EX	220-240	60-400	1 to 6	
Keytop	BP1000	220-240	1000	1 to 6	1 to 6
Khind	DS2500	220-240	500		1 to 1

Compatible Dimmer List

LED GX53

LED by
MEGAMAN®

		LR2205d		LR3307d	
Manufacturer	Model No.	Voltage (V)	Wattage (W)		
Kopp	80.33	230	40-400		1 to 5
Legrand	281 080	230	500		1 to 6
Legrand	ADWGL4	220-240	40-400	1 to 6	1 to 6
Legrand	ADW-GL6	230	60-600	1 to 6	1 to 6
Legrand	BMD 300	100-240	40-300	1 to 2	1 to 1
Legrand	Haut 100-1000VA	250	100-1000		1 to 6
Legrand	Mosaic	220-240	60-500	1 to 6	1 to 4
Legrand	Neptune 806 15	230	60-500		1 to 6
Legrand	YB-CZD	220	40-630		1 to 6
Leviton	BME04-2L	220	400	1 to 6	
LK	506DA117	230	20-300		1 to 6
Lumeo Domus	T39.07	230	7-110	1 to 4	
Lumex	LT1D450LS Series	200-240	5-450		1 to 6
Merlin Gurin	MGU351118	230	400		1 to 6
Merten	5722	230	60-600	1 to 6	1 to 6
Merten	5778	220-230	20-315	1 to 6	
MK	42804PL	230	40-250	1 to 6	1 to 6
MK	47352SL	230	60-450		1 to 5
MK	GX8051	220-240	40-500	1 to 6	3 to 3
MK	K1523WHILV	230	40-300		1 to 6
MK	K1526WHI	230	8-48		1 to 1

Compatible Dimmer List LED GX53

LED by
MEGAMAN®

		LR2205d		LR3307d	
Manufacturer	Model No.	Voltage (V)	Wattage (W)		
MK	K1527WHI	230	8-48	1 to 1	
MK	K4511LV	220-240	4-70(LED)	1 to 6	
MK	L/N1511	230	60-450	1 to 6	
MK	SX8051	240	40-500	1 to 6	
MK	SX8501	220-240	500	1 to 6	
National	WEC57515	220	40-500	1 to 4	
National	WEG57515	220-240	40-500	1 to 6	
National	WNG575253	220-240	60-600	5 to 6	
National	WNG6801	220-240	500	1 to 6	
Niko	09-013	230	60-300	1 to 6	
Niko	310-016	220-240	50-500	1 to 6	
Nortronic	ATD500 GLE	220-240	50-500	1 to 6	
Panasonic	WEJ57515	220	40-500	1 to 4	
Peha	431 HAN LED	230	6-120	1 to 3	
Peha	434	230	60-400	1 to 6	
Peha	435 HAN	230	60-600	1 to 6	
POL	CAT 1593M	220-240	500	1 to 6	
Relco	RM0736	220-240	60-500	1 to 6	
Richi	270.15	220	300	1 to 6	
Richmond	GRID400CFL	240	400	1 to 6	
Richmond	GRID500	240	40-500	1 to 6	

Compatible Dimmer List

LED GX53

				LR2205d	LR3307d
Manufacturer	Model No.	Voltage (V)	Wattage (W)		
Richmond	GRID700	240	75-700		1 to 1
Schneider	5510X	220	800		1 to 6
Schneider	C460	220-240	400	1 to 2	1 to 1
Schneider	GU6012	220-240	60-400	1 to 6	1 to 5
Schneider	LTD300	230	300		1 to 6
Schneider	SD300	220-240	300	1 to 6	1 to 6
Schneider	WDE002747	230	9-100	1 to 6	1 to 6
Sica	359901	220	100		1 to 2
Simen	Simen 55	150-250	40-150	1 to 3	1 to 1
Simon	45E101	220	500		1 to 6
Simon	75313-39	230	40-500	1 to 6	1 to 6
Simon	Simon..813	220-240	40-500	1 to 6	1 to 6
Soben	C8M2	200-250	630	1 to 6	1 to 5
Sisben	Sisben 86	220	15-200	1 to 6	
Switchlight	SW-316	220-240	500	1 to 6	1 to 3
T&J	P2017S	220-240	40-630	1 to 6	
TCL	KGM2	220-240	500	1 to 6	4 to 6
TCL	LM2	220	630	1 to 6	
Tedastar	45291	220	500		1 to 6
TLC	LV LMOD1	216-253	120		1 to 3
TLC	VL JP400MOD	230	10-250		1 to 6

Manufacturer	Model No.	Voltage (V)	Wattage (W)	LR2205d		LR3307d	
Varilight	JQP401W	230	10-400				1 to 6
Varilight	TQP501W	216-253	60-500				1 to 6
Venus	9720	220	40-900		1 to 6		1 to 2
Vi-ko	215	220-240	600		1 to 6		1 to 6
Vi-ko	90 30 48	220	600		1 to 6		
Vimar	Plana 14150	230	100-500		1 to 2		1 to 6
Vivian	D-21102	220-240	1000		1 to 6		1 to 6
Wilts	WPDIMWH401	230	7-40(LED)				1 to 5
Zano	ZGRID500	230	500		1 to 6		

Remarks:

The minimum and maximum numbers of LED lamp compatible depend upon the performance of the dimmer, which is subject to the status of the manufacturer's technology. Due to possible variations in country dimmer module specifications, please contact your local distributor for a list of compatible dimmers before installation.
Copyright © MEGAMAN® 2016. All rights reserved.

All the information contained within this publication was correct at the time of update and is subject to change without prior notice.
All other trademarks mentioned are the property of their respective owners.